



Battery Back-Up Device

PXST Series
Single Phase Standby UPS

Technical Documentation



ACCESSORY SOLD SEPARATELY

This series is a compact single phase standby UPS. It was designed to deliver protection to small routers, switches, desktop PCs, VoIP Equipment, phone systems, and point of sale equipment. A vital addition to any home office, it enables graceful shutdown of equipment during a longer power outage.

This series has plug and play functionality which means that this UPS is ready to start backing up your equipment right out of the box. Auto restart is standard so you won't need to be in the office after an outage occurs.

Key Specs

- **Available Models:**
400VA, 600VA, 800V
- **Floor, Desk, or Wall Mount**
- **Primary applications:**
Home or small office, desktop computers, routers, switches, and telecom closets

**See Ordering Information for model number selection*

Features

- Compact size and lightweight design
- RoHS compliant
- Plug & Play
- Auto Restart
- Cold Start Function

General Technical Specifications

Input Voltage	120VAC
Input Frequency	60Hz
Output Voltage	120VAC
Output Frequency	60Hz \pm 1Hz
Output Transfer time	2–6ms
Battery type	Sealed, maintenance free lead acid
Battery Recharge	8 hours to 90% capacity
UPS dimensions (W x D x H)	32x89x8.1 in (vertical stand position)
Line cord	5ft, 5–15P
Receptacles	(4) NEMA 5–15R
Operating temperature	32–104°F (0–40°C)
Humidity	0–90%
Altitude	11,500 ft above sea level
AC mode	Blue LED ON

Additional Photos



Ordering Information

MODEL	POWER RATING
PXST-400	400VA (240W)
PXST-600	600VA (360W)
PXST-800	800VA (480W)

ACCESSORIES

PSNMP-USB	External Web/SNMP Card
-----------	------------------------

KENICK
11400 47th St N Ste A
Clearwater, FL 33762
Phone: (800) 362-9997
www.KENICK.com



While every precaution has been taken to ensure accuracy and completeness herein, Kenick assumes no responsibility, and disclaims all liability, for damages resulting from use of this information or for any errors or omissions. Specifications are subject to change without notice.

Rev0 05-20